

208 VOLTS, 3 PHASE, 60 HERTZ

HP	0.25	0.33	0.5	0.75	1	1.5	2	3	5	7.5	10
*FLA	1.20	1.50	2.40	3.50	4.60	6.60	7.50	10.60	16.70	24.20	30.80
MCA	2.80	3.10	4.30	5.60	7.00	9.50	10.60	14.50	22.10	31.50	39.80
MCCP	3.70	4.40	6.40	8.90	11.40	15.90	17.90	24.90	38.60	55.50	70.30

HP	15	20	25	30	40	50	60	75	100	125
*FLA	46.20	59.40	74.80	88.00	114.00	143.00	169.00	211.00	273.00	343.00
MCA	59.00	75.50	94.80	111.30	143.80	180.00	212.50	265.00	342.50	430.00
MCCP	105.00	134.70	169.30	199.00	257.50	322.80	381.30	475.80	615.30	772.80

* FULL LOAD AMPS TAKEN FROM THE NATIONAL ELECTRICAL CODE, ARTICLE 430, TABLE 430:247-250. CONSULT THE NATIONAL ELECTRIC CODE (NFPA 70) FOR CONDUIT AND WIRE SIZING

<i>Weather-Rite LLC</i>	DRAWING DESCRIPTION		SCALE	TOLERANCES (UNLESS OTHERWISE NOTED)		
	1100 7 Mile Road, Comstock Park MI 49321-0700		WEIGHT (lbs):	FRACTION	MACH WELD FAB	
MATERIAL: NA		CHECKED BY:	DECIMAL	1/32	1/8	1/16
DO NOT SCALE DRAWING		REMOVE BURRS & SHARP EDGES	ANGLE	.01	.03	.02
ALL DIMENSIONS ARE IN INCHES UNLESS OTHERWISE SPECIFIED		BLANK SIZE (in):	1*	.005	2*	2*
This sheet is for general information purposes only. Information can change without notice and should therefore not be used for construction or installation. All products must be set-up, assembled, installed and used in accordance with all applicable instructions, the provided instruction manual as well as requirements of governmental authorities. The information on this sheet is proprietary.		DRAWN BY:	PRINTED DATE:	REV	CREATION DATE:	
		DWG. NO.	SHEET	1 OF 1		